

Mean Well Enclosed Switching Power Supply

	PRODUCT #	WEIGHT	OUTPUT									INPUT			PROTECTION	DIMENSION (mm)	PRICE	Buy Now	
			DC VOLTAGE	RATED CURRENT	CURRENT RANGE	RATED POWER	RIPPLE & NOISE (max.)	VOLTAGE ADJ. RANGE	VOLTAGE TOLERANCE	LINE REGULATION	LOAD REGULATION	FREQUENCY RANGE	EFFICIENCY (Typ.)	INRUSH CURRENT (Typ.)	LEAKAGE CURRENT				OVER VOLTAGE
1	RS-150-3.3	0.7Kg	3.3V	30A	0 ~ 30A	99W	80mVp-p	3.2V ~ 3.5V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	74%	COLD START 40A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	199X98X38	\$25.25	ADD TO CART
2	RS-150-5	0.7Kg	5V	26A	0 ~ 26A	130W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	199X98X38	\$25.25	ADD TO CART
3	RS-150-12	0.7Kg	12V	12.5A	0 ~ 12.5A	150W	120mVp-p	11.4 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83%	COLD START 40A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	199X98X38	\$25.25	ADD TO CART
4	RS-150-15	0.7Kg	15V	10A	0 ~ 10A	150W	120mVp-p	14.25 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84%	COLD START 40A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	199X98X38	\$25.25	ADD TO CART
5	RS-150-24	0.7Kg	24V	6.5A	0 ~ 6.5A	156W	120mVp-p	22.8 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 40A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	199X98X38	\$25.25	ADD TO CART
6	RS-150-48	0.7Kg	48V	3.3A	0 ~ 3.3A	158.4W	200mVp-p	45.6 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	87%	COLD START 40A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	199X98X38	\$25.25	ADD TO CART
7	RQ-125B (CH1)	0.7Kg	5V	11A	2 ~ 12A	120W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
8	RQ-125B (CH2)	0.7Kg	12V	4.5A	0.5 ~ 4.5A	120W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
9	RQ-125B (CH3)	0.7Kg	-5V	1A	0.1 ~ 1A	120W	80mVp-p	CH1: 4.75 ~ 5.5V	+6,-10%	(±)1.0%	(±)6.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
10	RQ-125B (CH4)	0.7Kg	-12V	0.5A	0 ~ 1A	120W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
11	RQ-125C (CH1)	0.7Kg	5V	10A	2 ~ 12A	122.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
12	RQ-125C (CH2)	0.7Kg	15V	4A	0.5 ~ 4A	122.5W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
13	RQ-125C (CH3)	0.7Kg	-5V	1A	0.1 ~ 1A	122.5W	80mVp-p	CH1: 4.75 ~ 5.5V	+6,-10%	(±)1.0%	(±)6.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
14	RQ-125C (CH4)	0.7Kg	-15V	0.5A	0 ~ 1A	122.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±) 2.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
15	RQ-125D (CH1)	0.7Kg	5V	8A	2 ~ 12A	124W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
16	RQ-125D (CH2)	0.7Kg	12V	2.5A	0.5 ~ 4A	124W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
17	RQ-125D (CH3)	0.7Kg	24V	2A	0.1 ~ 2.5A	124W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)5.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
18	RQ-125D (CH4)	0.7Kg	-12V	0.5A	0 ~ 1A	124W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$35.34	ADD TO CART
19	RQ-50B (CH1)	0.41Kg	5V	5A	0.5 ~ 6A	45.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	74%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
20	RQ-50B (CH2)	0.41Kg	12V	1A	0.2 ~ 1.5A	45.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	74%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
21	RQ-50B (CH3)	0.41Kg	-5V	0.5A	0 ~ 1A	45.5W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	74%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
22	RQ-50B (CH4)	0.41Kg	-12V	0.5A	0 ~ 1A	45.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	74%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
23	RQ-50C (CH1)	0.41Kg	5V	5A	0.5 ~ 6A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	75%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
24	RQ-50C (CH2)	0.41Kg	15V	1A	0.2 ~ 1.5A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	75%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
25	RQ-50C (CH3)	0.41Kg	-5V	0.5A	0 ~ 1A	50W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	75%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
26	RQ-50C (CH4)	0.41Kg	-15V	0.5A	0 ~ 1A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	75%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
27	RQ-50D (CH1)	0.41Kg	5V	3A	0.5 ~ 6A	53.4W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
28	RQ-50D (CH2)	0.41Kg	12V	0.9A	0.2 ~ 1.5A	53.4W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
29	RQ-50D (CH3)	0.41Kg	24V	0.9A	0.1 ~ 1A	53.4W	180mVp-p	CH1: 4.75 ~ 5.5V	+7,-5%	(±)2.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
30	RQ-50D (CH4)	0.41Kg	-12V	0.5A	0 ~ 1A	53.4W	80mVp	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$21.42	ADD TO CART
31	RQ-65B (CH1)	0.44Kg	5V	6A	0.5 ~ 8A	62.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART

32	RQ-65B (CH2)	0.44Kg	12V	2A	0.2 ~ 3A	62.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(+)9,-5%	(±)1.5%	(±)3.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
33	RQ-65B (CH3)	0.44Kg	-5V	0.5A	0 ~ 1A	62.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
34	RQ-65B (CH4)	0.44Kg	-12V	0.5A	0 ~ 1A	62.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
35	RQ-65C (CH1)	0.44Kg	5V	5A	0.5 ~ 8A	65W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
36	RQ-65C (CH2)	0.44Kg	15V	2A	0.2 ~ 3A	65W	120mVp-p	CH1: 4.75 ~ 5.5V	+10,-4%	(±)1.5%	(±)4.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
37	RQ-65C (CH3)	0.44Kg	-5V	0.5A	0 ~ 1A	65W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
38	RQ-65C (CH4)	0.44Kg	-15V	0.5A	0 ~ 1A	65W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
39	RQ-65D (CH1)	0.44Kg	5V	4A	0.5 ~ 8A	68W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
40	RQ-65D (CH2)	0.44Kg	12V	1.5A	0.2 ~ 3A	68W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
41	RQ-65D (CH3)	0.44Kg	24V	1A	0.1 ~ 1.5A	68W	180mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)2.0%	(±)5.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
42	RQ-65D (CH4)	0.44Kg	-12V	0.5A	0 ~ 1A	68W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38	\$23.87	ADD TO CART
43	RQ-85B (CH1)	0.6Kg	5V	7A	2 ~ 10A	80.7W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
44	RQ-85B (CH2)	0.6Kg	12V	3.1A	0.3 ~ 4A	80.7W	120mVp-p	CH1: 4.75 ~ 5.5V	+7,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
45	RQ-85B (CH3)	0.6Kg	-5V	0.5A	0 ~ 1A	80.7W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
46	RQ-85B (CH4)	0.6Kg	-12V	0.5A	0 ~ 1A	80.7W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
47	RQ-85C (CH1)	0.6Kg	5V	7A	2 ~ 10A	82.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
48	RQ-85C (CH2)	0.6Kg	15V	2.5A	0.3 ~ 4A	82.5W	120mVp-p	CH1: 4.75 ~ 5.5V	+3,-7%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
49	RQ-85C (CH3)	0.6Kg	-5V	0.5A	0 ~ 1A	82.5W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
50	RQ-85C (CH4)	0.6Kg	-15V	0.5A	0 ~ 1A	82.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
51	RQ-85D (CH1)	0.6Kg	5V	6A	2 ~ 10A	84W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
52	RQ-85D (CH2)	0.6Kg	12V	2A	0.3 ~ 4A	84W	120mVp-p	CH1: 4.75 ~ 5.5V	+7,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
53	RQ-85D (CH3)	0.6Kg	24V	1A	0.1 ~ 1.5A	84W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)5.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
54	RQ-85D (CH4)	0.6Kg	-12V	0.5A	0 ~ 1A	84W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$33.05	ADD TO CART
55	RS-100-3.3	0.6Kg	3.3V	20A	0 ~ 20A	66W	80mVp-p	3.2V ~ 3.5V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	74%	COLD START 40A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	159X97X38	\$24.15	ADD TO CART
56	RS-100-5	0.6Kg	5V	16A	0 ~ 16A	80W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	159X97X38	\$24.15	ADD TO CART
57	RS-100-12	0.6Kg	12V	8.5A	0 ~ 8.5A	102W	120mVp-p	11.4 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 40A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	159X97X38	\$24.15	ADD TO CART
58	RS-100-15	0.6Kg	15V	7A	0 ~ 7A	105W	120mVp-p	14.25 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	159X97X38	\$24.15	ADD TO CART
59	RS-100-24	0.6Kg	24V	4.5A	0 ~ 4.5A	108W	120mVp-p	22.8 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84%	COLD START 40A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	159X97X38	\$24.15	ADD TO CART
60	RS-100-48	0.6Kg	48V	2.3A	0 ~ 2.3A	110.4W	200mVp-p	45.6 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84%	COLD START 40A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	159X97X38	\$24.15	ADD TO CART
61	RS-15-3.3	0.13Kg	3.3V	3A	0 ~ 3A	9.9W	80mVp-p	2.9 ~ 3.6V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	72%	COLD START 65A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	62.5X51X28	\$9.49	ADD TO CART
62	RS-15-5	0.13Kg	5V	3A	0 ~ 3A	15W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 65A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	62.5X51X28	\$9.49	ADD TO CART
63	RS-15-12	0.13Kg	12V	1.3A	0 ~ 1.3A	15.6W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 65A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	62.5X51X28	\$9.49	ADD TO CART
64	RS-15-15	0.13Kg	15V	1A	0 ~ 1A	15W	120mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 65A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	62.5X51X28	\$9.49	ADD TO CART
65	RS-15-24	0.13Kg	24V	0.625A	0 ~ 0.625A	15W	200mVp-p	22 ~ 27.6V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 65A/230VAC	<2mA / 240VAC	28.4 ~ 32.4V	62.5X51X28	\$9.49	ADD TO CART
66	RS-15-48	0.13Kg	48V	0.313A	0 ~ 0.313A	15.024W	200mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 65A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	62.5X51X28	\$9.49	ADD TO CART
67	RS-25-3.3	0.2Kg	3.3V	6A	0 ~ 6A	19.8W	80mVp-p	2.85 ~ 3.6V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	73.5%	COLD START 30A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	78X51X28	\$12.08	ADD TO CART

68	RS-25-5	0.2Kg	5V	5A	0 ~ 5A	25W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78.5%	COLD START 30A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	78X51X28	\$12.08	ADD TO CART
69	RS-25-12	0.2Kg	12V	2.1A	0 ~ 2.1A	25.2W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81.5%	COLD START 30A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	78X51X28	\$12.08	ADD TO CART
70	RS-25-15	0.2Kg	15V	1.7A	0 ~ 1.7A	25.5W	120mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83.5%	COLD START 30A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	78X51X28	\$12.08	ADD TO CART
71	RS-25-24	0.2Kg	24V	1.1A	0 ~ 1.1A	26.4W	120mVp-p	22 ~ 27.6V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 30A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	78X51X28	\$12.08	ADD TO CART
72	RS-25-48	0.2Kg	48V	0.57A	0 ~ 0.57A	27.36W	200mVp-p	42 ~ 54V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	85%	COLD START 30A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	78X51X28	\$12.08	ADD TO CART
73	RS-35-3.3	0.3Kg	3.3V	7A	0 ~ 7A	23.1W	80mVp-p	2.9V ~ 3.6V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	76.5%	COLD START 36A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	99X82X36	\$13.00	ADD TO CART
74	RS-35-5	0.3Kg	5V	7A	0 ~ 7A	35W	80mVp-p	4.5 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	80.5%	COLD START 36A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	99X82X36	\$13.00	ADD TO CART
75	RS-35-12	0.3Kg	12V	3A	0 ~ 3A	36W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84.5%	COLD START 36A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	99X82X36	\$13.00	ADD TO CART
76	RS-35-15	0.3Kg	15V	2.4A	0 ~ 2.4A	36W	120mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 36A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	99X82X36	\$13.00	ADD TO CART
77	RS-35-24	0.3Kg	24V	1.5A	0 ~ 1.5A	36W	120mVp-p	22 ~ 27.6V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	88%	COLD START 36A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	99X82X36	\$13.00	ADD TO CART
78	RS-35-48	0.3Kg	48V	0.8A	0 ~ 0.8A	38.4W	200mVp-p	42 ~ 54V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	88.5%	COLD START 36A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	99X82X36	\$13.00	ADD TO CART
79	RS-50-3.3	0.41Kg	3.3V	10A	0 ~ 10A	33W	80mVp-p	3V ~ 3.6V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	78%	COLD START 33A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	99X97X36	\$14.54	ADD TO CART
80	RS-50-5	0.41Kg	5V	10A	0 ~ 10A	50W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	83%	COLD START 33A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	99X97X36	\$14.54	ADD TO CART
81	RS-50-12	0.41Kg	12V	4.2A	0 ~ 4.2A	50.4W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84.5%	COLD START 33A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	99X97X36	\$14.54	ADD TO CART
82	RS-50-15	0.41Kg	15V	3.4A	0 ~ 3.4A	51W	120mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 33A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	99X97X36	\$14.54	ADD TO CART
83	RS-50-24	0.41Kg	24V	2.2A	0 ~ 2.2A	52.8W	120mVp-p	22 ~ 27.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	88%	COLD START 33A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	99X97X36	\$14.54	ADD TO CART
84	RS-50-48	0.41Kg	48V	1.1A	0 ~ 1.1A	52.8W	200mVp-p	42 ~ 54V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	89%	COLD START 33A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	99X97X36	\$14.54	ADD TO CART
85	RS-75-3.3	0.41Kg	3.3V	15A	0 ~ 15A	49.5W	80mVp-p	3V ~ 3.6V	(±)3.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	75%	COLD START 40A/230VAC	<2mA / 240VAC	3.8 ~ 4.45V	129X97X38	\$17.29	ADD TO CART
86	RS-75-5	0.41Kg	5V	12A	0 ~ 12A	60W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	5.75 ~ 6.75V	129X97X38	\$17.29	ADD TO CART
87	RS-75-12	0.41Kg	12V	6A	0 ~ 6A	72W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84.5%	COLD START 40A/230VAC	<2mA / 240VAC	13.8 ~ 16.2V	129X97X38	\$17.29	ADD TO CART
88	RS-75-15	0.41Kg	15V	5A	0 ~ 5A	75W	120mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 40A/230VAC	<2mA / 240VAC	17.25 ~ 20.25V	129X97X38	\$17.29	ADD TO CART
89	RS-75-24	0.41Kg	24V	3.2A	0 ~ 3.2A	76.8W	120mVp-p	22 ~ 27.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	88.5%	COLD START 40A/230VAC	<2mA / 240VAC	27.6 ~ 32.4V	129X97X38	\$17.29	ADD TO CART
90	RS-75-48	0.41Kg	48V	1.6A	0 ~ 1.6A	76.8W	200mVp-p	42 ~ 54V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	89.5%	COLD START 40A/230VAC	<2mA / 240VAC	55.2 ~ 64.8V	129X97X38	\$17.29	ADD TO CART
91	RT-125A (CH1)	0.7Kg	5V	12A	2 ~ 15A	131W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
92	RT-125A (CH2)	0.7Kg	12V	5.5A	0.5 ~ 6A	131W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
93	RT-125A (CH3)	0.7Kg	-5V	1A	0.1 ~ 1A	131W	80mVp-p	CH1: 4.75 ~ 5.5V	+6,-10%	(±)1.0%	(±)6.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
94	RT-125B (CH1)	0.7Kg	5V	12A	2 ~ 15A	132W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
95	RT-125B (CH2)	0.7Kg	12V	5A	0.5 ~ 6A	132W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
96	RT-125B (CH3)	0.7Kg	-12V	1A	0.1 ~ 1A	132W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	80%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
97	RT-125C (CH1)	0.7Kg	5V	10A	2 ~ 15A	132.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	81%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
98	RT-125C (CH2)	0.7Kg	15V	4.5A	0.5 ~ 6A	132.5W	150mVp-p	CH1: 4.75 ~ 5.5V	+8,-3%	(±)1.0%	(±)3.0%	47 ~ 63Hz	81%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
99	RT-125C (CH3)	0.7Kg	-15V	1A	0.1 ~ 1A	132.5W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	81%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
100	RT-125D (CH1)	0.7Kg	5V	8A	2 ~ 15A	136W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
101	RT-125D (CH2)	0.7Kg	24V	3A	0.4 ~ 4A	136W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
102	RT-125D (CH3)	0.7Kg	12V	2A	0.1 ~ 2A	136W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	199X98X38	\$32.90	ADD TO CART
103	RT-65A (CH1)	0.44Kg	5V	6A	0.5 ~ 8A	66.1W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART

104	RT-65A (CH2)	0.44Kg	12V	2.8A	0.2 ~ 3.5A	66.1W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
105	RT-65A (CH3)	0.44Kg	-5V	0.5A	0 ~ 1A	66.1W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
106	RT-65B (CH1)	0.44Kg	5V	5A	0.5 ~ 8A	64.6W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
107	RT-65B (CH2)	0.44Kg	12V	2.8A	0.2 ~ 3.5A	64.6W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
108	RT-65B (CH3)	0.44Kg	-12V	0.5A	0 ~ 1A	64.6W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
109	RT-65C (CH1)	0.44Kg	5V	5A	0.5 ~ 8A	65.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
110	RT-65C (CH2)	0.44Kg	15V	2.2A	0.2 ~ 3A	65.5W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-4%	(±)1.5%	(±)3.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
111	RT-65C (CH3)	0.44Kg	-15V	0.5A	0 ~ 1A	65.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
112	RT-65D (CH1)	0.44Kg	5V	4A	0.5 ~ 8A	68W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
113	RT-65D (CH2)	0.44Kg	24V	1.5A	0.2 ~ 2A	68W	150mVp-p	CH1: 4.75 ~ 5.5V	+4,-6%	(±)1.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
114	RT-65D (CH3)	0.44Kg	12V	1A	0.1 ~ 1A	68W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)2.0%	(±)4.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129x98x38	\$22.80	ADD TO CART
115	RT-85A (CH1)	0.6Kg	5V	8A	2 ~ 10A	84.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
116	RT-85A (CH2)	0.6Kg	12V	3.5A	0.3 ~ 4A	84.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
117	RT-85A (CH3)	0.6Kg	-5V	0.5A	0 ~ 1A	84.5W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
118	RT-85B (CH1)	0.6Kg	5V	8A	2 ~ 10A	88W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
119	RT-85B (CH2)	0.6Kg	12V	3.5A	0.3 ~ 4A	88W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
120	RT-85B (CH3)	0.6Kg	-12V	0.5A	0 ~ 1A	88W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	76%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
121	RT-85C (CH1)	0.6Kg	5V	7A	2 ~ 10A	87.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
122	RT-85C (CH2)	0.6Kg	15V	3A	0.3 ~ 4A	87.5W	120mVp-p	CH1: 4.75 ~ 5.5V	+3,-7%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
123	RT-85C (CH3)	0.6Kg	-15V	0.5A	0 ~ 1A	87.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	77%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
124	RT-85D (CH1)	0.6Kg	5V	6A	2 ~ 10A	90W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
125	RT-85D (CH2)	0.6Kg	24V	2A	0.3 ~ 2.5A	90W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
126	RT-85D (CH3)	0.6Kg	12V	1A	0.1 ~ 1A	90W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)6.0%	47 ~ 63Hz	79%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38	\$31.98	ADD TO CART
127	NED-35A (CH1)	0.36Kg	5V	4A	0.5 ~ 5A	32W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	Call for Pricing Price Quote Form	
128	NED-35A (CH2)	0.36Kg	12V	1A	0.1 ~ 1.5A	32W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36		
129	NED-35B (CH1)	0.36Kg	5V	2.2A	0.5 ~ 4A	35W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36		
130	NED-35B (CH2)	0.36Kg	24V	1A	0.2 ~ 1.3A	35W	200mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36		
131	NED-50A (CH1)	0.44Kg	5V	6A	1 ~ 6A	54W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
132	NED-50A (CH2)	0.44Kg	12V	2A	0.3 ~ 3A	54W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
133	NED-50B (CH1)	0.44Kg	5V	4A	1 ~ 6A	53.6W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	82%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
134	NED-50B (CH2)	0.44Kg	24V	1.4A	0.2 ~ 2A	53.6W	200mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	82%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
135	NED-75A (CH1)	0.52Kg	5V	7A	1 ~ 8A	71W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
136	NED-75A (CH2)	0.52Kg	12V	3A	0.3 ~ 4A	71W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
137	NED-75B (CH1)	0.52Kg	5V	5A	1 ~ 6A	73W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
138	NED-75B (CH2)	0.52Kg	24V	2A	0.2 ~ 3A	73W	200mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
139	NES-15-5	0.18Kg	5V	3A	0 ~ 3A	15W	150mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)1.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	5.75 ~ 6.75V	78X51X28		
140	NES-15-12	0.18Kg	12V	1.3A	0 ~ 1.3A	15.6W	150mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 45A	<2mA /	13.8 ~ 16.2V	78X51X28		

															240VAC		
141	NES-15-15	0.18Kg	15V	1A	0 ~ 1A	15W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	17.25 ~ 20.25V	78X51X28
142	NES-15-24	0.18Kg	24V	0.7A	0 ~ 0.7A	16.8W	200mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	85%	COLD START 45A	<2mA / 240VAC	27.6 ~ 32.4V	78X51X28
143	NES-15-48	0.18Kg	48V	0.35A	0 ~ 0.35A	16.8W	240mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 45A	<2mA / 240VAC	55.2 ~ 64.8V	78X51X28
144	NES-25-5	0.3Kg	5V	5A	0 ~ 5A	25W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	5.75 ~ 6.75V	99X82X35
145	NES-25-12	0.3Kg	12V	2.1A	0 ~ 2.1A	25.2W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83%	COLD START 45A	<2mA / 240VAC	13.8 ~ 16.2V	99X82X35
146	NES-25-15	0.3Kg	15V	1.7A	0 ~ 1.7A	25.5W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	84%	COLD START 45A	<2mA / 240VAC	17.25 ~ 20.25V	99X82X35
147	NES-25-24	0.3Kg	24V	1.1A	0 ~ 1.1A	26.4W	200mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 45A	<2mA / 240VAC	27.6 ~ 32.4V	99X82X35
148	NES-25-48	0.3Kg	48V	0.57A	0 ~ 0.57A	27.36W	240mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 45A	<2mA / 240VAC	55.2 ~ 64.8V	99X82X35
149	NES-35-5	0.36Kg	5V	7A	0 ~ 7A	35W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	5.75 ~ 6.75V	99X97X36
150	NES-35-12	0.36Kg	12V	3A	0 ~ 3A	36W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	81%	COLD START 45A	<2mA / 240VAC	13.8 ~ 16.2V	99X97X36
151	NES-35-15	0.36Kg	15V	2.4A	0 ~ 2.4A	36W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83%	COLD START 45A	<2mA / 240VAC	17.25 ~ 20.25V	99X97X36
152	NES-35-24	0.36Kg	24V	1.5A	0 ~ 1.5A	36W	200mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	85%	COLD START 45A	<2mA / 240VAC	27.6 ~ 32.4V	99X97X36
153	NES-35-48	0.36Kg	48V	0.8A	0 ~ 0.8A	38.4W	240mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 45A	<2mA / 240VAC	55.2 ~ 64.8V	99X97X36
154	NES-50-5	0.41Kg	5V	10A	0 ~ 10A	50W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	5.75 ~ 6.75V	129X98X38
155	NES-50-12	0.41Kg	12V	4.2A	0 ~ 4.2A	50.4W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 45A	<2mA / 240VAC	13.8 ~ 16.2V	129X98X38
156	NES-50-15	0.41Kg	15V	3.4A	0 ~ 3.4A	51W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83%	COLD START 45A	<2mA / 240VAC	17.25 ~ 20.25V	129X98X38
157	NES-50-24	0.41Kg	24V	2.2A	0 ~ 2.2A	52.8W	200mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 45A	<2mA / 240VAC	27.6 ~ 32.4V	129X98X38
158	NES-50-48	0.41Kg	48V	1.1A	0 ~ 1.1A	52.8W	240mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	87%	COLD START 45A	<2mA / 240VAC	55.2 ~ 64.8V	129X98X38
159	NES-75-5	0.52Kg	5V	14A	0 ~ 14A	70W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	77%	COLD START 45A	<2mA / 240VAC	5.75 ~ 6.75V	159X97X38
160	NES-75-12	0.52Kg	12V	6.2A	0 ~ 6.2A	74.4W	120mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 45A	<2mA / 240VAC	13.8 ~ 16.2V	159X97X38
161	NES-75-15	0.52Kg	15V	5A	0 ~ 5A	75W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	83%	COLD START 45A	<2mA / 240VAC	17.25 ~ 20.25V	159X97X38
162	NES-75-24	0.52Kg	24V	3.2A	0 ~ 3.2A	76.8W	200mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	86%	COLD START 45A	<2mA / 240VAC	27.6 ~ 32.4V	159X97X38
163	NES-75-48	0.52Kg	48V	1.6A	0 ~ 1.6A	76.8W	240mVp-p	43.2 ~ 52.8V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 63Hz	87%	COLD START 45A	<2mA / 240VAC	55.2 ~ 64.8V	159X97X38
164	NET-35A (CH1)	0.36Kg	5V	3A	0.5 ~ 4A	29.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
165	NET-35A (CH2)	0.36Kg	12V	1A	0.1 ~ 1.5A	29.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
166	NET-35A (CH3)	0.36Kg	-5V	0.5A	0.1 ~ 0.5A	29.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
167	NET-35B (CH1)	0.36Kg	5V	3A	0.5 ~ 4A	33W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
168	NET-35B (CH2)	0.36Kg	12V	1A	0.1 ~ 1.5A	33W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
169	NET-35B (CH3)	0.36Kg	-12V	0.5A	0.1 ~ 0.5A	33W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
170	NET-35C (CH1)	0.36Kg	5V	2.5A	0.5 ~ 3.5A	35W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
171	NET-35C (CH2)	0.36Kg	15V	1A	0.1 ~ 1.5A	35W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
172	NET-35C (CH3)	0.36Kg	-15V	0.5A	0.1 ~ 0.5A	35W	150mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
173	NET-35D (CH1)	0.36Kg	5V	2.5A	0.5 ~ 3.5A	36.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
174	NET-35D (CH2)	0.36Kg	24V	0.5A	0.1 ~ 1A	36.5W	200mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
175	NET-35D (CH3)	0.36Kg	12V	1A	0.1 ~ 1A	36.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36
176	NET-50A (CH1)	0.44Kg	5V	4A	0.6 ~ 5A	46.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	76%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38

[Call for Pricing
Price Quote Form](#)

[Call for Pricing
Price Quote Form](#)

177	NET-50A (CH2)	0.44Kg	12V	2A	0.2 ~ 2.5A	46.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	76%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
178	NET-50A (CH3)	0.44Kg	-5V	0.5A	0.1 ~ 0.7A	46.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	76%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
179	NET-50B (CH1)	0.44Kg	5V	4A	0.6 ~ 5A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
180	NET-50B (CH2)	0.44Kg	12V	2A	0.2 ~ 2.5A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
181	NET-50B (CH3)	0.44Kg	-12V	0.5A	0.1 ~ 0.7A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
182	NET-50C (CH1)	0.44Kg	5V	4A	0.6 ~ 5A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
183	NET-50C (CH2)	0.44Kg	15V	1.5A	0.1 ~ 2A	50W	150mVp-p	CH1: 4.75 ~ 5.5V	(±) 8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
184	NET-50C (CH3)	0.44Kg	-15V	0.5A	0.1 ~ 0.7A	50W	150mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
185	NET-50D (CH1)	0.44Kg	5V	3A	0.6 ~ 5A	51W	80mVp-p	CH1: 4.75 ~ 5.5V	(±) 2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
186	NET-50D (CH2)	0.44Kg	24V	1A	0.1 ~ 1.5A	51W	200mVp-p	CH1: 4.75 ~ 5.5V	(±) 8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
187	NET-50D (CH3)	0.44Kg	12V	1A	0.1 ~ 1.5A	51W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	129X98X38		
188	NET-75A (CH1)	0.52Kg	5V	6A	0.6 ~ 7A	68.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
189	NET-75A (CH2)	0.52Kg	12V	3A	0.2 ~ 3.5A	68.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
190	NET-75A (CH3)	0.52Kg	-5V	0.5A	0.1 ~ 0.7A	68.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	77%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
191	NET-75B (CH1)	0.52Kg	5V	5A	0.6 ~ 7A	64.6W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
192	NET-75B (CH2)	0.52Kg	12V	2.8A	0.2 ~ 3.5A	64.6W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
193	NET-75B (CH3)	0.52Kg	-12V	0.5A	0.1 ~ 0.7A	64.6W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
194	NET-75C (CH1)	0.52Kg	5V	6A	0.6 ~ 7A	72W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
195	NET-75C (CH2)	0.52Kg	15V	2.3A	0.1 ~ 3.5A	72W	150mVp-p	CH1: 4.75 ~ 5.5V	(±) 8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
196	NET-75C (CH3)	0.52Kg	-15V	0.5A	0.1 ~ 0.7A	72W	150mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	78%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
197	NET-75D (CH1)	0.52Kg	5V	5A	0.6 ~ 6A	73W	80mVp-p	CH1: 4.75 ~ 5.5V	(±) 2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
198	NET-75D (CH2)	0.52Kg	24V	1.5A	0.1 ~ 2A	73W	200mVp-p	CH1: 4.75 ~ 5.5V	(±) 8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
199	NET-75D (CH3)	0.52Kg	12V	1A	0.1 ~ 1.5A	73W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 45A	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	159X97X38		
200	RT-50A (CH1)	0.41Kg	5V	4A	0.5 ~ 5A	46.5W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
201	RT-50A (CH2)	0.41Kg	12V	2A	0.2 ~ 2.5A	46.5W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
202	RT-50A (CH3)	0.41Kg	-5V	0.5A	0.1 ~ 1A	46.5W	100mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
203	RT-50B (CH1)	0.41Kg	5V	4A	0.5 ~ 5A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
204	RT-50B (CH2)	0.41Kg	12V	2A	0.2 ~ 2.5A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
205	RT-50B (CH3)	0.41Kg	-12V	0.5A	0.1 ~ 1A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	77%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
206	RT-50C (CH1)	0.41Kg	5V	4A	0.5 ~ 5A	50W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
207	RT-50C (CH2)	0.41Kg	15V	1.5A	0.2 ~ 2A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	+8,-4%	(±)1.5%	(±)3.0%	47 ~ 63Hz	78%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
208	RT-50C (CH3)	0.41Kg	-15V	0.5A	0.1 ~ 1A	50W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	78%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
209	RT-50D (CH1)	0.41Kg	5V	3A	0.5 ~ 5A	51W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)1.0%	47 ~ 63Hz	80%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
210	RT-50D (CH2)	0.41Kg	24V	1A	0.2 ~ 1.5A	51W	150mVp-p	CH1: 4.75 ~ 5.5V	+ 8,-4%	(±)2.0%	(±)3.0%	47 ~ 63Hz	80%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART
211	RT-50D (CH3)	0.41Kg	12V	1A	0.1 ~ 1A	51W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)2.0%	(±)4.0%	47 ~ 63Hz	80%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$20.20	ADD TO CART

[Call for Pricing](#)
[Price Quote Form](#)

	PRODUCT #	WEIGHT	OUTPUT									INPUT				PROTECTION	DIMENSION (mm)	PRICE	Buy Now
			DC VOLTAGE	RATED CURRENT	CURRENT RANGE	RATED POWER	RIPPLE & NOISE (max.)	VOLTAGE ADJ. RANGE	VOLTAGE TOLERANCE	LINE REGULATION	LOAD REGULATION	FREQUENCY RANGE	EFFICIENCY (Typ.)	INRUSH CURRENT (Typ.)	LEAKAGE CURRENT	OVER VOLTAGE			
212	RD-125A (CH1)	0.7Kg	5V	7.7A	2 ~ 15A	130.9W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X98X38	\$31.21	ADD TO CART
213	RD-125A (CH2)	0.7Kg	12V	7.7A	0.5 ~ 10A	130.9W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 63Hz	82%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X98X38	\$31.21	ADD TO CART
214	RD-125B (CH1)	0.7Kg	5V	4.6A	2 ~ 10A	133.4W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	85%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X98X38	\$31.21	ADD TO CART
215	RD-125B (CH2)	0.7Kg	24V	4.6A	0.4 ~ 5A	133.4W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 63Hz	85%	COLD START 40A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X98X38	\$31.21	ADD TO CART
216	RD-35A (CH1)	0.3Kg	5V	4A	0.3 ~ 4A	32W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)0.5%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
217	RD-35A (CH2)	0.3Kg	12V	1A	0.2 ~ 1A	32W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 6.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	79%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
218	RD-35B (CH1)	0.3Kg	5V	2.2A	0.3 ~ 4A	35W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)0.5%	47 ~ 63Hz	82%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
219	RD-35B (CH2)	0.3Kg	24V	1A	0.2 ~ 1.3A	35W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 5.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	82%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
220	RD-3513 (CH1)	0.3Kg	13.5V	1.3A	0.3 ~ 2A	35.1W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)4.0 %	(±)0.5%	(±)3.0%	47 ~ 63Hz	80%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
221	RD-3513 (CH2)	0.3Kg	-13.5V	1.3A	0.2 ~ 1.5A	35.1W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 4.0%	(±)0.5%	(±)3.0%	47 ~ 63Hz	80%	COLD START 36A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X82X36	\$16.83	ADD TO CART
222	RD-50A (CH1)	0.41Kg	5V	6A	0.3 ~ 6A	54W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)0.5%	47 ~ 63Hz	79%	COLD START 33A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$19.13	ADD TO CART
223	RD-50A (CH2)	0.41Kg	12V	2A	0.3 ~ 3A	54W	120mVp-p	CH1: 4.75 ~ 5.5V	(±) 7.0%	(±)1.5%	(±)3.0%	47 ~ 63Hz	79%	COLD START 33A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$19.13	ADD TO CART
224	RD-50B (CH1)	0.41Kg	5V	4A	0.3 ~ 6A	53.6W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0 %	(±)0.5%	(±)0.5%	47 ~ 63Hz	80%	COLD START 33A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$19.13	ADD TO CART
225	RD-50B (CH2)	0.41Kg	24V	1.4A	0.2 ~ 2A	53.6W	150mVp-p	CH1: 4.75 ~ 5.5V	-4,+8%	(±)1.5%	(±)3.0%	47 ~ 63Hz	80%	COLD START 33A/230VAC	<2mA / 240VAC	CH1: 5.75 ~ 6.75V	99X97X36	\$19.13	ADD TO CART