

Mean Well Open Frame Switching Power Supply

	PRODUCT #	WEIGHT	OUTPUT									INPUT			PROTECTION	DIMENSION (mm)	PRICE	Buy Now
			DC VOLTAGE	RATED CURRENT	CURRENT RANGE	RATED POWER	RIPPLE & NOISE (max.)	VOLTAGE ADJ. RANGE	VOLTAGE TOLERANCE	LINE REGULATION	LOAD REGULATION	FREQUENCY RANGE	EFFICIENCY (Typ.)	INRUSH CURRENT (Typ.)	OVER VOLTAGE			
1	<a href="#">MPD-45A (CH1)</a>	0.2Kg	5V	3.2A	0.4 ~ 5A	40W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	76%	COLD START 15A/115VAC	CH1: 5.75 ~ 6.75V	127X76X28	\$18.05	<a href="#">ADD TO CART</a>
2	<a href="#">MPD-45A (CH2)</a>	0.2Kg	12V	2A	0.2 ~ 2.5A	40W	120mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	76%	COLD START 15A/115VAC	CH1: 5.75 ~ 6.75V	127X76X28	\$18.05	<a href="#">ADD TO CART</a>
3	<a href="#">MPD-45B (CH1)</a>	0.2Kg	5V	3.2A	0.4 ~ 5A	44.8W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	78%	COLD START 15A/115VAC	CH1: 5.75 ~ 6.75V	127X76X28	\$18.05	<a href="#">ADD TO CART</a>
4	<a href="#">MPD-45B (CH2)</a>	0.2Kg	24V	1.2A	0.2 ~ 1.8A	44.8W	150mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	78%	COLD START 15A/115VAC	CH1: 5.75 ~ 6.75V	127X76X28	\$18.05	<a href="#">ADD TO CART</a>
5	<a href="#">MPD-65A (CH1)</a>	0.25Kg	5V	5.5A	0.4 ~ 7A	61.1W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75V	127X76X42	\$20.35	<a href="#">ADD TO CART</a>
6	<a href="#">MPD-65A (CH2)</a>	0.25Kg	12V	2.8A	0.2 ~ 3.2A	61.1W	150mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75V	127X76X42	\$20.35	<a href="#">ADD TO CART</a>
7	<a href="#">MPD-65B (CH1)</a>	0.25Kg	5V	3.5A	0.4 ~ 6A	65.5W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	78%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75V	127X76X42	\$20.35	<a href="#">ADD TO CART</a>
8	<a href="#">MPD-65B (CH2)</a>	0.25Kg	24V	2A	0.2 ~ 2.6A	65.5W	150mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	78%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75V	127X76X42	\$20.35	<a href="#">ADD TO CART</a>
9	<a href="#">MPS-45-3.3</a>	0.18Kg	3.3V	8A	0 ~ 10.7A	26.4W	80mVp-p	2.97 ~ 3.63V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	65%	COLD START 17A/115VAC	3.8 ~ 4.46V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
10	<a href="#">MPS-45-5</a>	0.18Kg	5V	8A	0 ~ 10.5A	40W	100mVp-p	4.5 ~ 5.5V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	72%	COLD START 17A/115VAC	5.75 ~ 6.75V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
11	<a href="#">MPS-45-7.5</a>	0.18Kg	7.5V	5.4A	0 ~ 7A	40.5W	100mVp-p	6.75 ~ 8.25V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	75%	COLD START 17A/115VAC	8.63 ~ 10.1V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
12	<a href="#">MPS-45-12</a>	0.18Kg	12V	3.7A	0 ~ 4.4A	44.4W	100mVp-p	10.8 ~ 13.2V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	76%	COLD START 17A/115VAC	13.8 ~ 16.2V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
13	<a href="#">MPS-45-13.5</a>	0.18Kg	13.5V	3.3A	0 ~ 3.9A	44.55W	100mVp-p	12.2 ~ 14.85V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	76%	COLD START 17A/115VAC	15.5 ~ 18.2V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
14	<a href="#">MPS-45-15</a>	0.18Kg	15V	3A	0 ~ 3.5A	45W	100mVp-p	13.5 ~ 16.5V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	77%	COLD START 17A/115VAC	17.25 ~ 20.25V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
15	<a href="#">MPS-45-24</a>	0.18Kg	24V	1.9A	0 ~ 2.2A	45.6W	100mVp-p	21.6 ~ 26.4V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	78%	COLD START 17A/115VAC	27.6 ~ 32.4V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
16	<a href="#">MPS-45-27</a>	0.18Kg	27V	1.7A	0 ~ 1.95A	45.9W	100mVp-p	24.3 ~ 29.7V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	78%	COLD START 17A/115VAC	31 ~ 36.45V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
17	<a href="#">MPS-45-48</a>	0.18Kg	48V	1A	0 ~ 1.1A	48W	100mVp-p	43.2 ~ 52.8V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	78%	COLD START 17A/115VAC	55.2 ~ 64.8V	127X76X28	\$17.14	<a href="#">ADD TO CART</a>
18	<a href="#">MPS-65-3.3</a>	0.23Kg	3.3V	12A	0 ~ 15.2A	39.6W	80mVp-p	2.97 ~ 3.63V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	66%	COLD START 17A/115VAC	3.8 ~ 4.46V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
19	<a href="#">MPS-65-5</a>	0.23Kg	5V	12A	0 ~ 13.8A	60W	100mVp-p	4.5 ~ 5.5V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	74%	COLD START 17A/115VAC	5.75 ~ 6.75V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
20	<a href="#">MPS-65-7.5</a>	0.23Kg	7.5V	8A	0 ~ 9.6A	60W	100mVp-p	6.75 ~ 8.25V	(±)3.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	76%	COLD START 17A/115VAC	8.63 ~ 10.1V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
21	<a href="#">MPS-65-12</a>	0.23Kg	12V	5.2A	0 ~ 6A	62.4W	100mVp-p	10.8 ~ 13.2V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	77%	COLD START 17A/115VAC	13.8 ~ 16.2V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
22	<a href="#">MPS-65-13.5</a>	0.23Kg	13.5V	4.7A	0 ~ 5.4A	63.45W	100mVp-p	12.2 ~ 14.85V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	78%	COLD START 17A/115VAC	15.5 ~ 18.2V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
23	<a href="#">MPS-65-15</a>	0.23Kg	15V	4.2A	0 ~ 4.8A	63W	100mVp-p	13.5 ~ 16.5V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	79%	COLD START 17A/115VAC	17.25 ~ 20.25V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
24	<a href="#">MPS-65-24</a>	0.23Kg	24V	2.7A	0 ~ 3A	64.8W	100mVp-p	21.6 ~ 26.4V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	80%	COLD START 17A/115VAC	27.6 ~ 32.4V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
25	<a href="#">MPS-65-27</a>	0.23Kg	27V	2.4A	0 ~ 2.7A	64.8W	100mVp-p	24.3 ~ 29.7V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	80%	COLD START 17A/115VAC	31 ~ 36.45V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
26	<a href="#">MPS-65-48</a>	0.23Kg	48V	1.35A	0 ~ 1.5A	64.8W	100mVp-p	43.2 ~ 52.8V	(±)2.0%	(±)1.0%	(±)2.0%	47 ~ 440Hz	80%	COLD START 17A/115VAC	55.2 ~ 64.8V	127X76X42	\$17.75	<a href="#">ADD TO CART</a>
27	<a href="#">MPT-45A (CH1)</a>	0.21Kg	5V	3A	0.4 ~ 5A	0 ~ 0.5A	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	73%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
28	<a href="#">MPT-45A (CH2)</a>	0.21Kg	12V	2A	0.2 ~ 2.5A	0 ~ 0.5A	120mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	73%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
29	<a href="#">MPT-45A (CH3)</a>	0.21Kg	-5V	0.3A	0 ~ 0.5A	0 ~ 0.5A	60mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	73%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
30	<a href="#">MPT-45B (CH1)</a>	0.21Kg	5V	3A	0.4 ~ 5A	0 ~ 0.5A	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
31	<a href="#">MPT-45B (CH2)</a>	0.21Kg	12V	2A	0.2 ~ 2.5A	0 ~ 0.5A	120mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
32	<a href="#">MPT-45B (CH3)</a>	0.21Kg	-12V	0.3A	0 ~ 0.5A	0 ~ 0.5A	100mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
33	<a href="#">MPT-45C (CH1)</a>	0.21Kg	5V	3A	0.4 ~ 5A	43.5W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
34	<a href="#">MPT-45C (CH2)</a>	0.21Kg	15V	1.6A	0.2 ~ 2.3A	43.5W	120mVp-p	CH1:4.5 ~ 5.5V	(±)7.0%	(±)2.0%	(±)4.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
35	<a href="#">MPT-45C (CH3)</a>	0.21Kg	-15V	0.3A	0 ~ 0.5A	43.5W	100mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	75%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X28	\$19.13	<a href="#">ADD TO CART</a>
36	<a href="#">MPT-65A (CH1)</a>	0.27Kg	5V	5.5A	0.4 ~ 7A	60W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
37	<a href="#">MPT-65A (CH2)</a>	0.27Kg	12V	2.5A	0.2 ~ 3.2A	60W	120mVp-p	CH1:4.5 ~ 5.5V	+10,-7%	(±)2.0%	(±)4.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
38	<a href="#">MPT-65A (CH3)</a>	0.27Kg	-5V	0.5A	0 ~ 0.7A	60W	60mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
39	<a href="#">MPT-65B (CH1)</a>	0.27Kg	5V	5.5A	0.4 ~ 7A	63.5W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
40	<a href="#">MPT-65B (CH2)</a>	0.27Kg	12V	2.5A	0.2 ~ 3.2A	63.5W	160mVp-p	CH1:4.5 ~ 5.5V	+10,-7%	(±)2.0%	(±)4.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
41	<a href="#">MPT-65B (CH3)</a>	0.27Kg	-12V	0.5A	0 ~ 0.7A	63.5W	100mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
42	<a href="#">MPT-65C (CH1)</a>	0.27Kg	5V	5.5A	0.4 ~ 7A	65W	60mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>
43	<a href="#">MPT-65C (CH2)</a>	0.27Kg	15V	2A	0.2 ~ 2.6A	65W	180mVp-p	CH1:4.5 ~ 5.5V	+10,-7%	(±)2.0%	(±)4.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>

44	<a href="#">MPT-65C (CH3)</a>	0.27Kg	-15V	0.5A	0 ~ 0.7A	65W	100mVp-p	CH1:4.5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	74%	COLD START 20A/115VAC	CH1: 5.75 ~ 6.75VDC	127X76X42	\$21.11	<a href="#">ADD TO CART</a>		
45	<a href="#">NFM-05-3.3</a>	0.03Kg	3.3V	1.25A	0 ~ 1.25A	4.125W	80mVp-p	3 ~ 3.63V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	67%	COLD START 25A/115VAC	3.8 ~ 4.95V	58X45X19.1	\$7.80	<a href="#">ADD TO CART</a>		
46	<a href="#">NFM-05-5</a>	0.03Kg	5V	1A	0 ~ 1A	5W	80mVp-p	4.5 ~ 5.5V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	71%	COLD START 25A/115VAC	5.75 ~ 6.75V	58X45X19.1	\$7.80	<a href="#">ADD TO CART</a>		
47	<a href="#">NFM-05-12</a>	0.03Kg	12V	0.42A	0 ~ 0.42A	5.04W	150mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	73%	COLD START 25A/115VAC	13.8 ~ 16.2V	58X45X19.1	\$7.80	<a href="#">ADD TO CART</a>		
48	<a href="#">NFM-05-15</a>	0.03Kg	15V	0.33A	0 ~ 0.33A	4.95W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	74%	COLD START 25A/115VAC	17.25 ~ 20.25V	58X45X19.1	\$7.80	<a href="#">ADD TO CART</a>		
49	<a href="#">NFM-05-24</a>	0.03Kg	24V	0.23A	0 ~ 0.23A	5.52W	240mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	76%	COLD START 25A/115VAC	27.6 ~ 32.4V	58X45X19.1	\$7.80	<a href="#">ADD TO CART</a>		
50	<a href="#">NFM-10-3.3</a>	0.045Kg	3.3V	2.5A	0 ~ 2.5A	8.25W	150mVp-p	3 ~ 3.63V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	66%	COLD START 25A/115VAC	3.8 ~ 4.95V	65X45X22	\$8.87	<a href="#">ADD TO CART</a>		
51	<a href="#">NFM-10-5</a>	0.045Kg	5V	2A	0 ~ 2A	10W	150mVp-p	4.5 ~ 5.5V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	74%	COLD START 25A/115VAC	5.75 ~ 6.75V	65X45X22	\$8.87	<a href="#">ADD TO CART</a>		
52	<a href="#">NFM-10-12</a>	0.045Kg	12V	0.85A	0 ~ 0.85A	10.2W	150mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	78%	COLD START 25A/115VAC	13.8 ~ 16.2V	65X45X22	\$8.87	<a href="#">ADD TO CART</a>		
53	<a href="#">NFM-10-15</a>	0.045Kg	15V	0.67A	0 ~ 0.67A	10.05W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	79%	COLD START 25A/115VAC	17.25 ~ 20.25V	65X45X22	\$8.87	<a href="#">ADD TO CART</a>		
54	<a href="#">NFM-10-24</a>	0.045Kg	24V	0.42A	0 ~ 0.42A	10.08W	240mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	79%	COLD START 25A/115VAC	27.6 ~ 32.4V	65X45X22	\$8.87	<a href="#">ADD TO CART</a>		
55	<a href="#">NFM-15-3.3</a>	0.065Kg	3.3V	3.5A	0 ~ 3.5A	11.55W	80mVp-p	3 ~ 3.63V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	73%	COLD START 30A/115VAC	3.8 ~ 4.95V	70X48X22	\$9.95	<a href="#">ADD TO CART</a>		
56	<a href="#">NFM-15-5</a>	0.065Kg	5V	3A	0 ~ 3A	15W	80mVp-p	4.5 ~ 5.5V	(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	76%	COLD START 30A/115VAC	5.75 ~ 6.75V	70X48X22	\$9.95	<a href="#">ADD TO CART</a>		
57	<a href="#">NFM-15-12</a>	0.065Kg	12V	1.25A	0 ~ 1.25A	15W	150mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	78%	COLD START 30A/115VAC	13.8 ~ 16.2V	70X48X22	\$9.95	<a href="#">ADD TO CART</a>		
58	<a href="#">NFM-15-15</a>	0.065Kg	15V	1A	0 ~ 1A	15W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	79%	COLD START 30A/115VAC	17.25 ~ 20.25V	70X48X22	\$9.95	<a href="#">ADD TO CART</a>		
59	<a href="#">NFM-15-24</a>	0.065Kg	24V	0.63A	0 ~ 0.63A	15.12W	240mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	81%	COLD START 30A/115VAC	27.6 ~ 32.4V	70X48X22	\$9.95	<a href="#">ADD TO CART</a>		
60	<a href="#">NFM-20-3.3</a>	0.09Kg	3.3V	4.5A	0 ~ 4.5A	14.85W	80mVp-p	3.1 ~ 3.6V	(±)2.0%	(±)1.0%	(±)1.5%	47 ~ 440Hz	71%	COLD START 30A/115VAC	3.8 ~ 4.46V	89X51X19.3	\$12.55	<a href="#">ADD TO CART</a>		
61	<a href="#">NFM-20-5</a>	0.09Kg	5V	4.4A	0 ~ 4.4A	22W	80mVp-p	4.5 ~ 5.4V	(±)2.0%	(±)1.0%	(±)1.5%	47 ~ 440Hz	75%	COLD START 30A/115VAC	5.75 ~ 6.75V	89X51X19.3	\$12.55	<a href="#">ADD TO CART</a>		
62	<a href="#">NFM-20-12</a>	0.09Kg	12V	1.8A	0 ~ 1.8A	21.6W	150mVp-p	10.8 ~ 13.2V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	81%	COLD START 30A/115VAC	13.8 ~ 16.2V	89X51X19.3	\$12.55	<a href="#">ADD TO CART</a>		
63	<a href="#">NFM-20-15</a>	0.09Kg	15V	1.4A	0 ~ 1.4A	21W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	83%	COLD START 30A/115VAC	17.25 ~ 20.25V	89X51X19.3	\$12.55	<a href="#">ADD TO CART</a>		
64	<a href="#">NFM-20-24</a>	0.09Kg	24V	0.92A	0 ~ 0.92A	22.08W	240mVp-p	21.6 ~ 26.4V	(±)1.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	84%	COLD START 30A/115VAC	27.6 ~ 32.4V	89X51X19.3	\$12.55	<a href="#">ADD TO CART</a>		
65	<a href="#">PM-05-3.3</a>	0.085Kg	3.3V	1.25A	0 ~ 1.25A	4.125W	80mVp-p		(±)3.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	67%	COLD START 25A/115VAC	3.8 ~ 4.95V	62.85x50x19.7	\$8.87	<a href="#">ADD TO CART</a>		
66	<a href="#">PM-05-5</a>	0.085Kg	5V	1A	0 ~ 1A	5W	80mVp-p		(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	71%	COLD START 25A/115VAC	5.75 ~ 6.75V	62.85x50x19.7	\$8.87	<a href="#">ADD TO CART</a>		
67	<a href="#">PM-05-12</a>	0.085Kg	12V	0.42A	0 ~ 0.42A	5.04W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	73%	COLD START 25A/115VAC	13.8 ~ 16.2V	62.85x50x19.7	\$8.87	<a href="#">ADD TO CART</a>		
68	<a href="#">PM-05-15</a>	0.085Kg	15V	0.33A	0 ~ 0.33A	4.95W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	74%	COLD START 25A/115VAC	17.25 ~ 20.25V	62.85x50x19.7	\$8.87	<a href="#">ADD TO CART</a>		
69	<a href="#">PM-05-24</a>	0.085Kg	24V	0.23A	0 ~ 0.23A	5.52W	240mVp-p		(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	76%	COLD START 25A/115VAC	27.6 ~ 32.4V	62.85x50x19.7	\$8.87	<a href="#">ADD TO CART</a>		
70	<a href="#">PM-10-3.3</a>	0.105Kg	3.3V	2.5A	0 ~ 2.5A	8.25W	150mVp-p		(±)3.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	66%	COLD START 25A/115VAC	3.8 ~ 4.95V	70X50X22.7	\$10.40	<a href="#">ADD TO CART</a>		
71	<a href="#">PM-10-5</a>	0.105Kg	5V	2A	0 ~ 2A	10W	150mVp-p		(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	74%	COLD START 25A/115VAC	5.75 ~ 6.75V	70X50X22.7	\$10.40	<a href="#">ADD TO CART</a>		
72	<a href="#">PM-15-12</a>	0.105Kg	12V	0.85A	0 ~ 0.85A	10.2W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	78%	COLD START 25A/115VAC	13.8 ~ 16.2V	70X50X22.7	\$10.40	<a href="#">ADD TO CART</a>		
73	<a href="#">PM-10-15</a>	0.105Kg	15V	0.67A	0 ~ 0.67A	10.05W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	79%	COLD START 25A/115VAC	17.25 ~ 20.25V	70X50X22.7	\$10.40	<a href="#">ADD TO CART</a>		
74	<a href="#">PM-10-24</a>	0.105Kg	24V	0.42A	0 ~ 0.42A	10.08W	240mVp-p		(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	79%	COLD START 25A/115VAC	27.6 ~ 32.4V	70X50X22.7	\$10.40	<a href="#">ADD TO CART</a>		
75	<a href="#">PM-15-3.3</a>	0.14Kg	3.3V	3.5A	0 ~ 3.5A	11.55W	80mVp-p		(±)3.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	73%	COLD START 30A/115VAC	3.8 ~ 4.95V	75x53x22.7	\$11.78	<a href="#">ADD TO CART</a>		
76	<a href="#">PM-15-5</a>	0.14Kg	5V	3A	0 ~ 3A	15W	80mVp-p		(±)2.0%	(±)1.0%	(±)1.0%	47 ~ 440Hz	76%	COLD START 30A/115VAC	5.75 ~ 6.75V	75x53x22.7	\$11.78	<a href="#">ADD TO CART</a>		
77	<a href="#">PM-15-12</a>	0.14Kg	12V	1.25A	0 ~ 1.25A	15W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	78%	COLD START 30A/115VAC	13.8 ~ 16.2V	75x53x22.7	\$11.78	<a href="#">ADD TO CART</a>		
78	<a href="#">PM-15-15</a>	0.14Kg	15V	1A	0 ~ 1A	15W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	79%	COLD START 30A/115VAC	17.25 ~ 20.25V	75x53x22.7	\$11.78	<a href="#">ADD TO CART</a>		
79	<a href="#">PM-15-24</a>	0.14Kg	24V	0.63A	0 ~ 0.63A	15.12W	240mVp-p		(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	81%	COLD START 30A/115VAC	27.6 ~ 32.4V	75x53x22.7	\$11.78	<a href="#">ADD TO CART</a>		
80	<a href="#">PM-20-3.3</a>	0.18Kg	3.3V	4.5A	0 ~ 4.5A	14.85W	80mVp-p		(±)3.0%	(±)1.0%	(±)1.5%	47 ~ 440Hz	71%	COLD START 30A/115VAC	3.8 ~ 4.46V	94X56X22.7	\$14.23	<a href="#">ADD TO CART</a>		
81	<a href="#">PM-20-5</a>	0.18Kg	5V	4.4A	0 ~ 4.4A	22W	80mVp-p		(±)2.0%	(±)1.0%	(±)1.5%	47 ~ 440Hz	75%	COLD START 30A/115VAC	5.75 ~ 6.75V	94X56X22.7	\$14.23	<a href="#">ADD TO CART</a>		
82	<a href="#">PM-20-12</a>	0.18Kg	12V	1.8A	0 ~ 1.8A	21.6W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	81%	COLD START 30A/115VAC	13.8 ~ 16.2V	94X56X22.7	\$14.23	<a href="#">ADD TO CART</a>		
83	<a href="#">PM-20-15</a>	0.18Kg	15V	1.4A	0 ~ 1.4A	21W	150mVp-p		(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 440Hz	83%	COLD START 30A/115VAC	17.25 ~ 20.25V	94X56X22.7	\$14.23	<a href="#">ADD TO CART</a>		
84	<a href="#">PM-20-24</a>	0.18Kg	24V	0.92A	0 ~ 0.92A	22.08W	240mVp-p		(±)2.0%	(±)0.5%	(±)0.5%	47 ~ 440Hz	84%	COLD START 30A/115VAC	27.6 ~ 32.4V	94X56X22.7	\$14.23	<a href="#">ADD TO CART</a>		
85	<a href="#">RPD-160B (CH1)</a>	0.33Kg	5V	12A	1 ~ 12A	150.4W	80mVp-p	CH1: 5 ~ 5.5V	(±)2.5%	(±)0.5%	(±)1.5%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$57.83	<a href="#">ADD TO CART</a>		
86	<a href="#">RPD-160B (CH2)</a>	0.33Kg	24V	3.6A	0.2 ~ 3.6A	150.4W	200mVp-p	CH1: 5 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$57.83	<a href="#">ADD TO CART</a>		
87	<a href="#">RPDG-160B</a>								[5V STANDBY (G model):5VSB: 5V@0.6A w/o fan, 0.8A with fan 20.5CFM ; tolerance 2%, ripple: 50mVp-p(max.)] [PS-ON INPUT SIGNAL: Power on: PS-ON = "Hi" or " > 2 ~ 5V" ; Power off: PS-ON = "Low" or " < 0 ~ 0.5V" ] [ 5Vsb & no load power cons. < 0.75 W ]										\$64.41	<a href="#">ADD TO CART</a>
88	<a href="#">RPD-60A (CH1)</a>	0.15Kg	5V	5A	0.5 ~ 5.5A	49W	80mVp-p		+3,-2%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>		
89	<a href="#">RPD-60A (CH2)</a>	0.15Kg	12V	2A	0.1 ~ 2.2A	49W	80mVp-p		(±)6.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	78%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>		
90	<a href="#">RPD-60B (CH1)</a>	0.15Kg	5V	3.5A	0.5 ~ 3.85A	53.5W	80mVp-p		+3,-2%	(±)0.5%	(±)1.5%	47 ~ 63Hz	82%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>		

91	<a href="#">RPD-60B (CH2)</a>	0.15Kg	24V	1.5A	0.1 ~ 1.65A	53.5W	100mVp-p		+8,-4%	(±)1.0%	(±)2.0%	47 ~ 63Hz	82%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
92	<a href="#">RPD-75A (CH1)</a>	0.25Kg	5V	7A	1 ~ 9.5A	71W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127x76.2x31	\$25.51	<a href="#">ADD TO CART</a>
93	<a href="#">RPD-75A (CH2)</a>	0.25Kg	12V	3A	0.3 ~ 4A	71W	120mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127x76.2x31	\$25.51	<a href="#">ADD TO CART</a>
94	<a href="#">RPD-75B (CH1)</a>	0.25Kg	5V	5A	1 ~ 6.8A	73W	80mVp-p	CH1: 4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127x76.2x31	\$25.51	<a href="#">ADD TO CART</a>
95	<a href="#">RPD-75B (CH2)</a>	0.25Kg	24V	2A	0.2 ~ 2.7A	73W	200mVp-p	CH1: 4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127x76.2x31	\$25.51	<a href="#">ADD TO CART</a>
96	<a href="#">RPS-160-5</a>	0.32Kg	5V	30A	0 ~ 30A	155W	100mVp-p	CH1:4.5 ~ 5.5V	(±)4.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	85%	COLD START 35A/115VAC	5.75 ~ 6.75V	127X76.2X34.6	\$50.50	<a href="#">ADD TO CART</a>
97	<a href="#">RPS-160-12</a>	0.32Kg	12V	12.9A	0 ~ 12.9A	159.8W	100mVp-p	CH1:10.8 ~ 13.2V	(±)3.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	87%	COLD START 35A/115VAC	13.8 ~ 16.2V	127X76.2X34.6	\$50.50	<a href="#">ADD TO CART</a>
98	<a href="#">RPS-160-15</a>	0.32Kg	15V	10.3A	0 ~ 10.3A	159.5W	120mVp-p	CH1:13.5 ~ 16.5V	(±)3.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	87%	COLD START 35A/115VAC	17.25 ~ 20.25V	127X76.2X34.6	\$50.50	<a href="#">ADD TO CART</a>
99	<a href="#">RPS-160-24</a>	0.32Kg	24V	6.5A	0 ~ 6.5A	161W	150mVp-p	CH1:22 ~ 27V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	87%	COLD START 35A/115VAC	27.6 ~ 32.4V	127X76.2X34.6	\$50.50	<a href="#">ADD TO CART</a>
100	<a href="#">RPS-160-48</a>	0.32Kg	48V	3.25A	0 ~ 3.25A	161W	250mVp-p	CH1:43.2 ~ 52.8V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	88%	COLD START 35A/115VAC	55.2 ~ 64.8V	127X76.2X34.6	\$50.50	<a href="#">ADD TO CART</a>
101	<a href="#">RPSG-160-5</a>	G: With 5Vsb & no load power consumption < 0.75 W [Blank: Basic function (without 5Vsb)]															\$56.61	<a href="#">ADD TO CART</a>
102	<a href="#">RPSG-160-12</a>	5V STANDBY (G model): 5VSB : 5V@0.6A without fan, 0.8A with fan 20.5CFM ; tolerance 2%, ripple : 50mVp-p(max.) PS-ON INPUT SIGNAL (G model): Power on: PS-ON = "Hi" or " > 2 ~ 5V" ; Power off: PS-ON = "Low" or " < 0 ~ 0.5V"															\$56.61	<a href="#">ADD TO CART</a>
103	<a href="#">RPSG-160-15</a>																\$56.61	<a href="#">ADD TO CART</a>
104	<a href="#">RPSG-160-24</a>																\$56.61	<a href="#">ADD TO CART</a>
105	<a href="#">RPSG-160-48</a>																\$56.61	<a href="#">ADD TO CART</a>
106	<a href="#">RPS-60-3.3</a>	0.15Kg	3.3V	10A	0 ~ 11A	33W	80mVp-p	3.1 ~ 3.6V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	74%	COLD START 60A/230VAC	3.8 ~ 5V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
107	<a href="#">RPS-60-5</a>	0.15Kg	5V	10A	0 ~ 11A	50W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	79%	COLD START 60A/230VAC	5.75 ~ 6.75V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
108	<a href="#">RPS-60-12</a>	0.15Kg	12V	5A	0 ~ 5.5A	60W	120mVp-p	11.4 ~ 13.2V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	83%	COLD START 60A/230VAC	13.8 ~ 16.2V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
109	<a href="#">RPS-60-15</a>	0.15Kg	15V	4A	0 ~ 4.4A	60W	150mVp-p	13.5 ~ 16.5V	(±)2.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	84%	COLD START 60A/230VAC	17.25 ~ 20.25V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
110	<a href="#">RPS-60-24</a>	0.15Kg	24V	2.5A	0 ~ 2.75A	60W	240mVp-p	22.8 ~ 27.6V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	85%	COLD START 60A/230VAC	28.4 ~ 32.4V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
111	<a href="#">RPS-60-48</a>	0.15Kg	48V	1.25A	0 ~ 1.375A	60W	300mVp-p	45.6 ~ 52.8V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	86%	COLD START 60A/230VAC	55.2 ~ 64.8V	101.6X50.8X29	\$17.60	<a href="#">ADD TO CART</a>
112	<a href="#">RPS-75-3.3</a>	0.26Kg	3.3V	15A	0 ~ 20A	49.5W	80mVp-p	2.9 ~ 3.6V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	73%	COLD START 25A/115VAC	3.8 ~ 4.46V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
113	<a href="#">RPS-75-5</a>	0.26Kg	5V	14A	0 ~ 18.7A	70W	80mVp-p	4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 25A/115VAC	5.75 ~ 6.75V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
114	<a href="#">RPS-75-12</a>	0.26Kg	12V	6.3A	0 ~ 8.3A	75.6W	120mVp-p	11.4 ~ 13.2V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	82%	COLD START 25A/115VAC	13.8 ~ 16.2V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
115	<a href="#">RPS-75-15</a>	0.26Kg	15V	5A	0 ~ 6.7A	75W	150mVp-p	13.5 ~ 16.5V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	83%	COLD START 25A/115VAC	17.25 ~ 20.25V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
116	<a href="#">RPS-75-24</a>	0.26Kg	24V	3.2A	0 ~ 4.2A	76.8W	240mVp-p	22.8 ~ 27.6V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	85%	COLD START 25A/115VAC	27.6 ~ 32.4V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
117	<a href="#">RPS-75-36</a>	0.26Kg	36V	2.1A	0 ~ 2.8A	75.6W	300mVp-p	34.2 ~ 39.6V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	86%	COLD START 25A/115VAC	41.4 ~ 48.6V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
118	<a href="#">RPS-75-48</a>	0.26Kg	48V	1.6A	0 ~ 2.1A	76.8W	300mVp-p	45.6 ~ 52.8V	(±)1.0%	(±)0.5%	(±)1.0%	47 ~ 63Hz	86%	COLD START 25A/115VAC	55.2 ~ 64.8V	127X76.2X31	\$23.72	<a href="#">ADD TO CART</a>
119	<a href="#">RPT-160A (CH1)</a>	0.33Kg	5V	14A	0.6 ~ 14A	145W	100mVp-p	CH1:5 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
120	<a href="#">RPT-160A (CH2)</a>	0.33Kg	12V	5.5A	0.2 ~ 5.5A	145W	120mVp-p	CH1:5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
121	<a href="#">RPT-160A (CH3)</a>	0.33Kg	-5V	1A	0.1 ~ 1A	145W	120mVp-p	CH1:5 ~ 5.5V	-5,+7%	(±)1.0%	-5,+6%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
122	<a href="#">RPT-160B (CH1)</a>	0.33Kg	5V	14A	0.6 ~ 14A	146W	100mVp-p	CH1:5 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
123	<a href="#">RPT-160B (CH2)</a>	0.33Kg	12V	5A	0.2 ~ 5A	146W	120mVp-p	CH1:5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
124	<a href="#">RPT-160B (CH3)</a>	0.33Kg	-12V	1A	0.1 ~ 1A	146W	120mVp-p	CH1:5 ~ 5.5V	-4,+5%	(±)1.0%	-4,+5%	47 ~ 63Hz	84%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
125	<a href="#">RPT-160C (CH1)</a>	0.33Kg	5V	14A	0.6 ~ 14A	143W	100mVp-p	CH1:5 ~ 5.5V	(±)2.0%	(±)0.5%	(±)2.0%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
126	<a href="#">RPT-160C (CH2)</a>	0.33Kg	15V	3.6A	0.1 ~ 3.6A	143W	150mVp-p	CH1:5 ~ 5.5V	(±)4.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
127	<a href="#">RPT-160C (CH3)</a>	0.33Kg	-15V	1A	0.1 ~ 1A	143W	150mVp-p	CH1:5 ~ 5.5V	(±)8.0%	(±)1.0%	(±)8.0%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
128	<a href="#">RPT-160D (CH1)</a>	0.33Kg	5V	11A	0.3 ~ 11A	147.8W	100mVp-p	CH1:5 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
129	<a href="#">RPT-160D (CH2)</a>	0.33Kg	12V	5A	0.2 ~ 5A	147.8W	120mVp-p	CH1:5 ~ 5.5V	(±)5.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
130	<a href="#">RPT-160D (CH3)</a>	0.33Kg	24V	1.2A	0.15 ~ 1.2A	147.8W	200mVp-p	CH1:5 ~ 5.5V	+7,-5%	(±)1.0%	-3,+4%	47 ~ 63Hz	83%	COLD START 35A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X34.6	\$60.59	<a href="#">ADD TO CART</a>
131	<a href="#">RPTG-160A</a>	5V STANDBY (G model): 5VSB : 5V@0.6Awithout fan, 0.8Awith fan 20.5CFM ; tolerance 2%, ripple : 50mVp-p(max.) PS-ON INPUT SIGNAL (G model): Power on: PS-ON = "Hi" or " > 2 ~ 5V" ; Power off: PS-ON = "Low" or " < 0 ~ 0.5V"															\$67.47	<a href="#">ADD TO CART</a>
132	<a href="#">RPTG-160B</a>	G: With 5Vsb & no load power consumption < 0.75 W Blank: Basic function (without 5Vsb)															\$67.47	<a href="#">ADD TO CART</a>
133	<a href="#">RPTG-160C</a>																\$67.47	<a href="#">ADD TO CART</a>
134	<a href="#">RPTG-160D</a>																\$67.47	<a href="#">ADD TO CART</a>
135	<a href="#">RPT-60A (CH1)</a>	0.15Kg	5V	4A	0.5 ~ 4.4A	46.5W	80mVp-p		+3,-2%	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
136	<a href="#">RPT-60A (CH2)</a>	0.15Kg	12V	2A	0.1 ~ 2.2A	46.5W	80mVp-p		(±)6.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	77%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
137	<a href="#">RPT-60A (CH3)</a>	0.15Kg	-5V	0.5A	0.1 ~ 0.55A	46.5W	80mVp-p		+9,-8%	(±)1.0%	+5,-7%	47 ~ 63Hz	77%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
138	<a href="#">RPT-60B (CH1)</a>	0.15Kg	5V	4A	0.5 ~ 4.4A	50W	80mVp-p		+3,-2%	(±)0.5%	(±)1.5%	47 ~ 63Hz	78%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>

139	<a href="#">RPT-60B (CH2)</a>	0.15Kg	12V	2A	0.1 ~ 2.2A	50W	80mVp-p		(±)6.0%	(±)1.0%	(±)2.0%	47 ~ 63Hz	78%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
140	<a href="#">RPT-60B (CH3)</a>	0.15Kg	-12V	0.5A	0.1 ~ 0.55A	50W	100mVp-p		+10,-6%	(±)2.0%	(±)5.0%	47 ~ 63Hz	78%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
141	<a href="#">RPT-60C (CH1)</a>	0.15Kg	5V	4A	0.5 ~ 4.4A	50W	80mVp-p		+3,-2%	(±)0.5%	(±)1.5%	47 ~ 63Hz	79%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
142	<a href="#">RPT-60C (CH2)</a>	0.15Kg	15V	1.5A	0.1 ~ 1.65A	50W	100mVp-p		(±)6.0%	(±)2.0%	(±)3.0%	47 ~ 63Hz	79%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
143	<a href="#">RPT-60C (CH3)</a>	0.15Kg	-15V	0.5A	0.1 ~ 0.55A	50W	150mVp-p		(±)8.0%	(±)2.0%	(±)4.0%	47 ~ 63Hz	79%	COLD START 60A/230VAC	CH1: 5.75 ~ 6.75V	101.6X50.8X29	\$18.36	<a href="#">ADD TO CART</a>
144	<a href="#">RPT-75A (CH1)</a>	0.26Kg	5V	6A	0.6 ~ 8A	68.5W	80mVp-p	CH1:4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	76%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
145	<a href="#">RPT-75A (CH2)</a>	0.26Kg	12V	3A	0.2 ~ 4A	68.5W	120mVp-p	CH1:4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	76%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
146	<a href="#">RPT-75A (CH3)</a>	0.26Kg	-5V	0.5A	0.1 ~ 1A	68.5W	120mVp-p	CH1:4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	76%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
147	<a href="#">RPT-75B (CH1)</a>	0.26Kg	5V	6A	0.6 ~ 8A	72W	80mVp-p	CH1:4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
148	<a href="#">RPT-75B (CH2)</a>	0.26Kg	12V	3A	0.2 ~ 4A	72W	120mVp-p	CH1:4.75 ~ 5.5V	(±)6.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
149	<a href="#">RPT-75B (CH3)</a>	0.26Kg	-12V	0.5A	0.1 ~ 1A	72W	120mVp-p	CH1:4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
150	<a href="#">RPT-75C (CH1)</a>	0.26Kg	5V	6A	0.6 ~ 8A	72W	80mVp-p	CH1:4.75 ~ 5.5V	(±)2.0%	(±)0.5%	(±)1.5%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
151	<a href="#">RPT-75C (CH2)</a>	0.26Kg	15V	2.3A	0.1 ~ 3A	72W	150mVp-p	CH1:4.75 ~ 5.5V	(±)8.0%	(±)1.0%	(±)3.0%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>
152	<a href="#">RPT-75C (CH3)</a>	0.26Kg	-15V	0.5A	0.1 ~ 1A	72W	150mVp-p	CH1:4.75 ~ 5.5V	(±)5.0%	(±)1.0%	(±)1.0%	47 ~ 63Hz	77%	COLD START 25A/115VAC	CH1: 5.75 ~ 6.75V	127X76.2X31	\$26.47	<a href="#">ADD TO CART</a>